



marantz

CINEMA 30

CINEMA 30 AV Receiver

CINEMA 30 is the most refined AVR Marantz has created. With premium features, optimized from decades of rich heritage, timeless style, and engineered for utmost performance, Marantz CINEMA 30 is the foundation of superior home theater systems.

- **High Power & Low Distortion**
Each channel is rated at 140W with 0.05% THD, making both powerful dynamics and subtle detail a reality.
- **11 Channels & Countless Configurations**
Though 11 amplifier channels are built in, CINEMA 30 can process up to 13.4 channels, making the perfect speaker layout for your room easy to achieve.
- **No Compromise Engineering**
Hi-Fi performance technologies like HDAM SA-2, monolithic symmetrical amplifiers, toroidal transformer-based power supplies, and more elevate CINEMA 30 to performance levels seldom found in an AVR.
- **Sound Master Tuned & Calibrated for You**
Premium and custom ingredients are chosen by the Marantz Sound Masters to capture The Most Musical Sound. Powerful calibration and tuning tools are included, enabling you to get the best performance from your system.
- **Compatibility**
7 HDMI inputs, plus digital, analog, and phono inputs – even analog video plus loudspeaker and pre-amp outputs – ensure connectivity to virtually any components you have.
- **Timeless Yet Modern Style**
Excellence is heard and seen. CINEMA 30 is meticulously crafted in Japan with authentic materials in a modern style, befitting its rich heritage and stunning performance.



The Most Musical Sound

CINEMA 30

Technical Specifications

Multichannel Surround		
DTS HD Master / DTS:X / DTS:X Pro / DTS Neo:6 / DTS Neural:X/ DTS Virtual:X	Yes / Yes / Yes / No / Yes / Yes	
IMAX Enhanced	Yes	
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization / Dolby Atmos Music / Dolby ProLogic II / Dolby Surround	Yes / Yes / Yes Yes / No / Yes	
Auro 3D	Yes	
360 Reality Audio / MPEG H	Yes / Yes	
Audyssey DSX	No	
Multichannel Stereo	Yes	
Max. Number of Processing (Preamp) Channels	13.4	
Sound Enhancements		
Discrete Power Amplifier	Yes	
Copper Plated Chassis	Yes	
Power Transformer: Toroidal / EI	Toroidal	
Current Feedback Topology	Yes	
Hyper Dynamic Amplifier Modules (HDAM)	Yes	
Pure Direct	Yes	
Gold Plated RCA Terminals	Yes	
Clock Jitter Reducer	Yes	
Audyssey	MultEQ XT32	
Audyssey Dynamic EQ / Dynamic Volume / Audyssey LFC	Yes / Yes / Yes	
Dirac Live upgradability	Yes	
Compressed Audio Enhancer: MDAX2	Yes	
Network		
HEOS Multi-Room and Streaming	Yes	
Bluetooth Re-Transmit for Bluetooth headphones	Yes (with volume control)	
Alexa / Google Voice Assistant / Apple HomePod	Yes / Yes / Yes	
Network Audio Sharing	Yes	
Lossy Formats: MP3 / WMA / AAC	Yes / Yes / Yes	
Lossless Formats: FLAC / ALAC / WAV	Yes / Yes / Yes	
Lossless formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	Yes / Yes / Yes	
DSD Audio Streaming	Yes, 2.8/5.6 MHz	
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	Yes / Yes / Yes	
Gapless Playback	Yes (FLAC, WAV, ALAC, DSD)	
AirPlay Audio Streaming	Yes (AirPlay 2)	
Internet Radio	Yes (Tuneln)	
Spotify	Yes (Spotify Connect)	
Pandora / SiriusXM	Yes / Yes	
Other Streaming Services	Amazon Music HD / Amazon Music / TIDAL / Deezer / iHeart Radio / Napster / Soundcloud / Mood Mix	
Roon tested	Yes	
Compatible with Remote App for Smart Phones	Marantz AVR Remote	
Compatible with Remote App for Tablets	Android / iOS / Amazon Kindle	
Wi-Fi / Bluetooth / Ethernet Ports	Yes / Yes / Yes	
HDMI		
HDMI Inputs: Back / Front	Yes	
HDCP 2.3 Support	Yes	
HDMI Outputs: Main / Zone	Yes	
Video Conversion Analog → HDMI	Yes	
Analog to HDMI Scaling	Yes	
HDMI to HDMI Scaling	Yes	
GUI Overlay on HDMI	Yes	
HDMI 2.1: 8K/60Hz AB / 4K/120Hz AB	Yes	
8K/60Hz AB / 4K/120Hz AB Pass-through In/Out	Yes	
HDMI 2.0: 3D / 4K / CEC / ARC	Yes	
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR	Yes	
HDMI		
ALLM (Auto Low Latency Mode) Pass-through for Gaming	Yes	
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching	Yes / Yes / No	
3D Signal Pass-through	Yes	
8K Signal Pass-through / Scaling / GUI Overlay	Yes / Yes / Yes	
4K Signal Pass-through / Scaling / GUI Overlay	Yes / Yes / Yes	
HDMI Pass-through in Standby Mode	Yes	
Picture Adjust / Noise Reduction	No / No	
CEC	Yes	
DSD Audio Capability	Yes	
Audio Return Channel	ARC, eARC	
Auto LipSync	Yes	



Multiroom / CI		
HEOS Multi-Room Integrated		Yes
HEOS Link Compatibility: IR / IP		Yes / Yes
Multi-Room zones		3
Zone Audio Source: HDMI / Opt. Coax / Network, USB / Analog		Yes (2ch) / Yes (2ch) / Yes / Yes
Zone Audio Output: Speaker / Preout		Yes / Yes
Zone HDMI Output from HDMI Source		Yes
IP Control / RS232 Control / Web Control / App Control		Yes / Yes / Yes / Yes
IR Flasher In		Yes
Marantz Remote Bus		Yes
DC Trigger Output		3
HDMI Diagnostics		Yes
Inputs/Outputs		
Video	Composite In / Out	2 / 0
	Component In / Out	1 / 0
	HDMI In / Out	7 / 3
	Multi-Room Video Out: Video / HDMI	No / Yes
Audio	Analog In / Out	6 / 0
	Phono (MM) In	Yes
	Digital In: Optical / Coaxial	2 / 2
	Multi-Room Out: Analog / Digital	2 / 0
	Multichannel Pre Out	Yes (13.4)
	Subwoofer Out	4 (independent)
	7.1 Multichannel Input	No
	Other	
Other	Speaker Terminal: Gold Plated Screw / Regular Screw	Yes / No
	Number of Speaker Terminals	13
	Speaker A / B	Assignable
	Bi-Amp Drive	Assignable
	Multi-Room Speaker Terminal	Assignable
	Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	No / No / No / No / Yes
	USB Audio / Made for iPod / Made for iPhone	Yes / No / No
	USB Power supply on rear panel	Yes
	AM/FM Tuner	Yes
Specifications		
Number of Poweramps		11
Power Output	8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive	N/A
	8 ohm, 20 Hz - 20 kHz, 0.05% 2ch Drive	140 W
	6 ohm, 1 kHz, 0.7% 2ch Drive	175 W
	6 ohm, 1 kHz, 10% 1ch Drive	250 W
70% Guarantee		Yes
Others		
Auto Speaker Setup by Microphone		Audyssey MultEQ XT32 Dirac Live (upgrade)
Front Display		2 line FLD + port hole OLED
Graphic User Interface - GUI		Modern HD GUI
ISF Certification		No
GUI Languages		3
Setup Assistant		Yes
Smart Select		Yes
Firmware Update by Network / USB		Yes / Yes
Variable Crossover / Optimized Bass Redirection / Bass Sync		Yes / Yes / Yes
ECO Mode / Auto Power Off / Sleep Timer		Yes / Yes / Yes
General		
Metal Front Panel		Yes
System Remote Control		RC051SR
Pre-Programmed / Learnable / LCD Display		Yes /
		Yes / Yes
Consumption	Power	780 W
	Power, No Sound (ECO on / off)	65 W / 110 W
	Standby	0.2 W
	CEC Standby	0.5 W
	Network Standby	Less than 2.0 W
Maximum Dimensions	Antenna, Horizontal: (W × D × H)	17.4 × 18.0 × 7.5 in.
	Antenna, Vertical: (W × D × H)	17.4 × 18.0 × 10.2 in.
	w/o Antenna: (W × D × H)	17.4 × 17.6 × 7.5 in.
What's in the box	Main unit, remote control, batteries, AM/FM antennas, wire labels, quick start guide, Audyssey microphone, cardboard microphone stand, 2 External Detachable Antennas, AC cord	
Weight in lbs.		42.8
UPC		747192140434 (U1B)
		747192140441 (U1SG)

Design and specifications are subject to change by Marantz without notice.

www.marantz.com